



## *Gas Grill Lighting Instructions*

1. Connect the propane gas hose assembly and regulator to the cylinder and tighten. Turn the burners to the OFF position.
2. Open the propane cylinder valve and check all connections for leaks with a soap and water solution.
3. CAUTION: If hood is being used, open before attempting to light the grill.
4. Turn the crossover ignition burner control knob to the HI position. Insert BBQ lighter into ignition hole on right hand side of BBQ and light. That should ignite the burner.

If burner fails to ignite, turn the gas off, wait five(5) minutes. Then try to light again.

5. Once the crossover burner is lit, any main burner may be lit by simply turning the knob for each burner to the HI position.

### **SHUT DOWN**

1. Close the cylinder valve and allow burners to burn out the gas in the line and manifold.
2. Turn all the control valves to the OFF position.
3. Disconnect the grill from the propane cylinder.